

# GF1NF2W-0.4/6

0.4-6GHz 2-Way Power Divider

## Performance:

|                        |                                                |
|------------------------|------------------------------------------------|
| 频率范围 Frequency Range   | 0.4~6 GHz                                      |
| 插入损耗 Insertion Loss    | $\leq 1.2$ dB (excluding 3dB theoretical loss) |
| 输入驻波 Input VSWR        | $\leq 1.25$ Typ.1.20                           |
| 输出驻波 Output VSWR       | $\leq 1.20$ Typ.1.15                           |
| 隔离度 Isolation          | $\geq 20$ dB Typ.28dB                          |
| 幅度平衡 Amplitude Balance | $\pm 0.2$ dB                                   |
| 相位平衡 Phase Balance     | $\pm 2^\circ$                                  |
| 功率容量 Power Handling    | 30W(Divider) , 2W (Combiner)                   |
| 接口形式 Connectors        | N-Female                                       |
| 表面处理 Surface Finish    | Conductive oxidation                           |

## Size: (mm/[inch])

