

GF2SF4W-0/8

DC-8GHz 4 Way Power divider

Performance:

频率范围 Frequency Range	DC-8 GHz
插入损耗 Insertion Loss	≤ 13.0 dB
输入驻波 VSWR	≤ 1.20
幅度平衡 Amplitude Balance	± 0.8 dB
相位平衡 Phase Balance	$\pm 6^\circ$
功率容量 Power Handling	1 W
接口形式 Connectors	SMA-Female
表面处理 Surface Finish	Conductive oxidation

Size: (Unit: mm)

